

## **CLAIM AMENDMENTS**

### **Claim Amendment Summary**

#### **Claims pending**

- At time of the Action: Claims 20, 30, 41-52, and 55.
- After this Response: Claims 20, 30, 41-52, and 55.

**Canceled or Withdrawn claims:** none.

**Amended claims:** none.

**New claims:** none.

### **Claims:**

Claims 1-19 are CANCELED.

20. (PREVIOUSLY PRESENTED) A method of generating encrypted analog first, second and third signals (R', G', B', respectively) from first, second, and third analog input signals (R,G,B, respectively) the method comprising:

pseudo-randomly generating at least one of a plurality of matrix coefficients, a1, a2, a3, b1, b2, b3, c1, c2, c3;

using an encryption circuit to perform a matrix multiplication operation to generate the encrypted analog first, second, and third signals, according to the following equations:

$$R' = a1R + b1G + c1B,$$

$$G' = a2R + b2G + c2B,$$

421 West Riverside, Suite 500  
Spokane, WA 99201  
P: 509.324.9256  
F: 509.323.8979  
www.leeandhayes.com  
**lee & hayes**

Serial No.: 09/609,019

Atty Docket No.: MS1-847US

RESPONSE TO NON-FINAL OFFICE ACTION DATED

2

0830041249 C:\MS1-01847us\MS1-847us.m02.doc

atty: Kasey C. Christie

$$B' = a3R + b3G + c3B;$$

wherein the matrix coefficients are generated such that each of the R', G' and B' signals will be the product of summing two signals in the set of analog signals R, G, B and subtracting one of the signals in the set of analog signals R, G, B.

Claims 21-29 are CANCELED.

30. (PREVIOUSLY PRESENTED) A communication method comprising the steps of:

using a pseudo-random number generator to generate output values; and  
modifying first, second and third signals, by performing a matrix multiplication operation thereon utilizing matrix coefficients which are a function of at least one of the pseudo-random output values, the modified first, second and third signals being encrypted analog signals so as to define first, second and third encrypted analog signals; and

transmitting the first, second and third encrypted analog signals to a destination device;

wherein said matrix multiplication involves summing an integer multiple of two of the first, second and third signals and subtracting an integer multiple of another one of said first second and third signals to produce the first encrypted analog signal.

Claims 31-40 are CANCELED.

421 West Riverside, Suite 500  
Spokane, WA 99201  
P: 509.324-9256  
F: 509.323-8979  
www.lee&hayes.com  
**lee & hayes**

1 41. (ORIGINAL) A method of decrypting encrypted analog signals  
2 including the steps of:

3 generating a first decrypted analog signal from a first pair of  
4 encrypted analog signals by:

5 summing the two encrypted analog signals in the first  
6 pair of analog signals to produce a first sum; and

7 dividing the first sum by a first value to produce a first  
8 decrypted analog signal.

9 42. (ORIGINAL) The method of claim 41, further comprising:

10 generating a second decrypted analog signal from a second pair of  
11 encrypted analog signals by:

12 summing the two encrypted analog signals in the  
13 second pair of analog signals to produce a second sum; and

14 dividing the second sum by a second value to produce  
15 a second decrypted analog signal.

16 43. (ORIGINAL) The method of claim 42, further comprising:

17 generating a third decrypted analog signal from a third pair of  
18 encrypted analog signals by:

19 summing the two encrypted analog signals in the third pair of  
20 analog signals to produce a third sum; and

21 dividing the third sum by a third value to produce a third  
22 decrypted analog signal.  
23  
24  
25

421 West Riverside, Suite 500  
Spokane, WA 99201  
P: 509 324-9256  
F: 509 323-8979  
www.lee&hayes.com  
**lee & hayes**

1           44. (ORIGINAL) The method of claim 43, wherein the first second and  
2 third values are the same.

3  
4           45. (ORIGINAL) The method of claim 44, wherein the first second and  
5 third values are integer multiples of 2.

6  
7           46. (ORIGINAL) The method of claim 44, further comprising the step  
8 of:

9                 periodically changing the value used for the first, second and third  
10 values as a function of the output of a pseudo random number generator.

11  
12           47. (ORIGINAL) The method of claim 41, further comprising:  
13                 comparing values in first and second rows of values to identify a  
14 first column of values in which the first and second rows of values include the  
15 same value; and

16                 controlling which one of a plurality of output lines the first  
17 decrypted analog signal is transmitted on as a function of the identified column of  
18 values.

19  
20           48. (ORIGINAL) The method of claim 43, further comprising:  
21                 comparing values in first and second rows of values to identify a first  
22 column in which the first and second rows of values include the same value;

23                 comparing values in second and third rows of values to identify a second  
24 column in which the second and third rows of values include the same value, the  
25 second column being different than said first column;

Serial No.: 09/609,019

Atty Docket No.: MS1-847US

RESPONSE TO NON-FINAL OFFICE ACTION DATED

5

0830041249 G:\MS1-01847\MS1-847\us.m02.doc

atty: Kasey C. Christo

1 and

2 controlling which one of a plurality of output lines the first decrypted  
3 analog signal is transmitted on as a function of the identified first column and  
4 which one of the plurality of output lines the second decrypted analog signal is  
5 transmitted on as a function of the identified second column, the first and Second  
6 decrypted analog signals being transmitted on different output lines.

7  
8 49. (ORIGINAL) The method of claim 48, wherein the first and second  
9 rows of values are first and second rows of values included in a permutation  
10 matrix used to encrypt the analog signals included in the first pair of signals.

11  
12 50. (ORIGINAL) The method of claim 48, further comprising:  
13 comparing, values in a third row of values and  
14 said first row of values to identify a third column in which the third and  
15 first rows of values include the same value;

16 and

17 controlling which one of a plurality of output lines the third decrypted  
18 analog signal is transmitted on as a function of the identified third column, the  
19 third decrypted analog signal being transmitted on a different output line from said  
20 first and second decrypted analog signals.

21  
22 51. (PREVIOUSLY PRESENTED) The method of claim 49, wherein  
23 the first and second rows of values are first and second rows of values included in  
24 a permutation matrix used to encrypt the analog signals included in the first pair of  
25 signals;

1 wherein the second and third rows of values are Second and third  
2 rows of values included in said permutation matrix; and

3 wherein the third and first rows of values are third and first rows of  
4 Values included in said permutation matrix.

5  
6 52. (ORIGINAL) The method of claim 48,

7 wherein the first, second and third decrypted analog signals are red,  
8 green and blue analog video signals; and

9 wherein the plurality of output lines include red, green and blue  
10 output lines which are coupled to a display device.

11  
12 53. (CANCELLED)

13  
14 54. (CANCELLED)

15  
16 55. (PREVIOUSLY PRESENTED) A method of generating an  
17 encrypted analog signal from at least two of a first analog input signal, a second  
18 analog input signal, and a third analog input signal, the method comprising:

19 pseudo-randomly generating an encryption value;

20 multiplying a first one of said first, second, and third analog input signals  
21 with said encryption value to produce a multiplied signal; and

22 combining said multiplied signal with at least a second signal generated  
23 from a second one of said first, second, and third analog input signals to produce

24 said encrypted analog signal;

25 wherein said encryption value is a matrix coefficient and wherein said  
matrix multiplication operation is performed using analog multipliers.

421 West Riverside, Suite 500  
Spokane, WA 99201  
P: 509.324-9256  
F: 509.323-8979  
www.leeandhayes.com  
**lee & hayes**